

Avionics

IFR 4000 Nav/Comm Test Set



AEROFLEX
A passion for performance.

The IFR 4000 is a compact, lightweight and weatherproof unit designed for testing ILS, VOR, Marker Beacon and VHF/UHF Communications avionics systems.

- Accurate measurement of VHF/UHF transmitter, frequency, output power, modulation (AM and FM and receiver sensitivity)
- Accurate measurement of HF transmitter, frequency, output power, modulation (AM and SSB USB/LSB) receiver sensitivity
- Generation of ARINC 596 Selective Calling Tones
- Accurate measurement of HF/VHF/UHF antenna and or feeder SWR (Standing Wave Ratio)
- Simulation of Localizer and Glideslope (CAT I, II and III Ground Station) Signals with variable DDM settings
- Swept Localizer DDM for coupled Auto Pilot testing (Simultaneous Localizer, Glideslope and Marker signals)
- Simulation of VOR beacon with variable bearing
- Simulation of Marker Beacon, Selectable Airways (Z), Outer and Middle Marker Tones
- Accurate measurement of 121.5/243 MHz emergency beacon transmitter frequency, output power, modulation (AM). Headphone audio output to monitor swept tone (Option 1 required)
- Accurate measurement of 406 MHz COSPAS/SARSAT emergency beacon transmitter frequency, output power. Decode and display of all location and user protocols (Option 1 required)
- Guided Test capability cuts down total test time
- 5.7 inch LCD display with user adjustable backlight and contrast
- Internal battery allows eight hours of operation before recharge

The IFR 4000 verifies the operation and installation of ILS, VOR and Marker Beacon receivers and VHF/UHF AM/FM and HF AM/SSB transceivers.

The IFR 4000, with its lightweight size (under 8 lbs.), long run time battery (8 hrs) and ergonomic design, will provide the user with the most portable navigational communications ramp test set on the market today. Cockpit and bench use testing can be easily interchanged. The menu driven functionality and guided test capability make this instrument extremely easy to use. Combine these benefits with the outstanding price and the user has an instrument that delivers total value.

The IFR 4000 is designed to provide test support for ramp or bench environments by utilizing the supplied trimode antenna for over the air measurements or direct connection to the unit's RF I/O port.

VOR provides signal generation over the VOR band of 108.00 to 117.95 MHz with 30 Hz variable phase and 9960 Hz (sub-carrier frequency modulated with 30 Hz reference phase) amplitude modulated at 30% per tone. VOR bearing selection is provided in pre-set steps of 30 degrees and variable steps of 0.1 degrees.

Localizer provides signal generation over the Localizer band of 108.10 to 111.95 MHz with 90 Hz and 150 Hz tones, amplitude modulated at 20% per tone. Variable and fixed DDM control is provided.

Glideslope provides signal generation over the Glideslope band of

329.15 to 335.00 MHz with 90 Hz and 150 Hz tones, amplitude modulated at 40% per tone. Variable and fixed DDM control is provided.

Marker Beacon provides 75 MHz signal generation, amplitude modulated at 95% with selectable 400, 1300 and 3000 Hz tones.

ILS provides simultaneous Localizer (with swept DDM), Glideslope and Marker Beacon signals.

COMM AM provides signal generation and monitoring of transmitter power and modulation depth over the range of 10.0000 to 400.0000 MHz. A 1020 Hz tone, amplitude modulated at 30% is also provided. Frequency control is provided in 8.33 kHz / 25 kHz channel steps or 1 kHz variable steps.

COMM FM provides signal generation and monitoring of transmitter power and FM deviation over the range of 10.0000 to 400.0000 MHz. A 1000 Hz tone, frequency modulated at 5 kHz deviation is also provided. Frequency control is provided in 25/12.5 kHz channel steps or 1 kHz variable steps.

COMM SSB provides signal generation and monitoring of transmitter power and modulation depth over the range of 10.0000 to 30.0000 MHz. A 1000 Hz tone or variable tone 25 to 3000 Hz, SSB modulated (LSB or USB), is also provided. Frequency control is provided in 100 Hz steps.

SWR provides selected CW frequency, SWR measurement or swept SWR measurement over a 10.0000 to 400.0000 MHz range.

SELCAL (Selective Calling) provides selectable consecutive tone pulse pairs which may be sent continuously or as a burst (VHF AM) for testing SELCAL decoders.

MORSE CODE provides 1 - 4 characters transmitted in the VOR and ILS localizer mode.

FREQUENCY COUNTER provides external frequency measurement over the RF I/O connector and ANT connector from 10 to 400 MHz and over the AUX connector from 1 to 10 MHz.

121.5/243 BCN provides monitoring for 121.5/243 MHz swept tone short range emergency beacons including monitoring of transmitter power, frequency, AM modulation depth, modulation swept tone start and stop frequencies. A headphone receive audio output is provided via the Aux Port (requires user manufactured adapter cable).

406 BCN provides monitoring for 406 MHz COPAS/SARSAT Emergency Locator Transmitter (ELT), Emergency Position Indicating Radio Beacons (EPIRB and Personal Locator) PLB Beacons including transmitter frequency and power. The beacon utilizes BPSK data to transmit position information derived from a long range navigation system or GPS receiver. All protocols defined in COSPAS/SARSAT G.005 Issue 2 Rev 1 are supported. They consist of 6 user protocols (plus a test protocol), 5 location protocols (plus a test protocol). The Protocol management and data field decode is automatically handled by the IFR 4000. Transmitter frequency and power are monitored.

SPECIFICATION

NOTE: A 15 minute warm-up period is required for all specifications.

RF SIGNAL GENERATOR

OUTPUT FREQUENCY

| | |
|-------------------------------|--|
| Marker Beacon Channel | 72.0 to 78.0 MHz in 25 kHz steps |
| Marker Beacon Pre-set | 74.5, 75.0 or 75.5 MHz |
| Marker Beacon Variable | 72.0 to 78.0 MHz in 1 kHz steps |
| VOR Channel | 108.0 to 117.95 MHz in 50 kHz steps |
| VOR Pre-set | 108.0, 108.05 or 117.95 MHz |
| VOR Variable | 107.0 to 118.0 MHz in 1 kHz steps |
| LOC Channel | 108.1 to 111.95 MHz in 50 kHz steps |
| LOC Pre-set | 108.1, 108.15 or 110.15 MHz |
| LOC Variable | 107.0 to 113.0 MHz in 50 kHz steps |
| G/S Channel | 329.15 to 335.0 MHz in 50 kHz steps |
| G/S Pre-set | 334.25, 334.55 or 334.70 MHz |
| G/S Variable | 327.0 to 337.0 MHz in 1 kHz steps |
| Comm AM Channel | 10.0000 to 400.0000 MHz in 25 kHz steps, 118.0000 to 156.0000 in 8.33 kHz steps |
| Comm AM Preset | 118.00, 137.00 or 156.00 MHz (VHF Band) 225.00, 312.00, 400.00 MHz (UHF Band) |
| Comm AM Variable | 10.0000 to 400.0000 MHz in 1 kHz steps |
| Comm FM Channel | 10.0000 to 400.0000 MHz in 12.5 or 25 kHz steps |
| Comm FM Pre-set | 156.00, 165.00 or 174.00 MHz |
| Comm FM Variable | 10.0000 to 400.0000 MHz in 1 kHz steps |
| Comm SSB Channel | 10.0000 to 30.0000 MHz in 100 Hz steps |
| SELCAL Channel | 118.0 to 156.0 MHz in 25 kHz steps |
| SELCAL Pre-set | 118.0, 137.0 or 156.0 MHz |
| SELCAL Variable | 117.0 to 157.0 MHz in 1 kHz steps |

FREQUENCY ACCURACY

Same as time base

OUTPUT LEVEL

ANTENNA CONNECTOR

Single Carrier

10 MHz to 75 MHz

-17 to -67 dBm in 0.5 dB steps

75 MHz to 400 MHz

+13 to -67 dBm in 0.5 dB steps

Accuracy

±3 dB

Dual Mode - LOC

0 dBm fixed

Accuracy

±2.5 dB

Dual Mode - G/S

0 to -76 dBm in 0.5 dB steps

Accuracy

±3 dB

Tri-Mode - Marker

+13 dBm fixed

Accuracy

±2 dB

Tri-Mode - LOC

-7 dBm fixed

Accuracy

±2 dB

Tri-Mode - G/S

-7 to -83 dBm in 0.5 dB steps

Accuracy

±3 dB

RF I/O CONNECTOR**Single Carrier****10 MHz to 75 MHz**

-40 to -130 dBm in 0.5 dB steps

75 MHz to 400 MHz

-12 to -130 dBm in 0.5 dB steps

Accuracy**-12 to -39.5 dBm**

±2.5 dB

-40 to -94.5 dBm

±2.0 dB

-95 to -120 dBm

±3 dB

Dual Mode - LOC

-22 dBm fixed

Accuracy

±2 dB

Dual Mode - G/S

-22 to -101 dBm in 0.5 dB steps

-22 to -100 dBm

±2.5 dB

SPECTRAL PURITY**HARMONICS**

<-20 dBc

NON-HARMONIC SPURIOUS

<-35 dBc between 10 and 400 MHz

VOR MODE**VOR TONE FREQUENCY ACCURACY**

| | |
|------------------------|--------|
| 30 Hz Reference | ±0.02% |
| 30 Hz Variable | ±0.02% |
| 1020 Hz | ±0.02% |
| 9960 Hz | ±0.02% |

AM MODULATION**CAL**

30, 1020 and 9960 Hz tones

30% AM, each tone

1020 Hz Morse code

10% AM

Accuracy

±2% modulation

Variable**Range**

0% to 55% AM (30, 9960 and 1020 Hz tones)

Distortion

<2.0 % in CAL position

FM MODULATION

30 Hz reference at ±480 Hz peak deviation on 9960 Hz sub-carrier

Accuracy

±25 Hz peak deviation

BEARING

To - From selectable

Preset Bearing

0°, 30°, 60°, 90°, 120°, 150°, 180°, 210°, 240°, 270°, 300°, and 330°

Variable Bearing

3600 digitally derived courses in 0.1° increments

Accuracy

±0.1°

LOC MODE**LOC TONE FREQUENCY ACCURACY**

| | |
|---------|--------|
| 90 Hz | ±0.02% |
| 150 Hz | ±0.02% |
| 1020 Hz | ±0.02% |

MODULATION**CAL****90 and 150 Hz Tones** 20% AM each tone**1020 Hz Audio Tone** 30% AM**1020 Hz Morse Tone** 10% AM**Accuracy** ±2% modulation**Variable****Range**

0% to 28% AM (90 and 150 Hz Tones)

0 to 42% AM (1020 Hz tone)

Distortion

<2.5% in CAL position

LOC DDM**Fixed****Range**

±0, 0.093, 0.155 or 0.200 DDM and tone delete

Accuracy

±0.0015 DDM (±1.5 µA) ±3% of setting (≤+10 dBm output level)

Variable**Range**

±0.4 in 0.001 DDM steps

Accuracy

±0.0025 DDM (±2.5 µA) ±3% of setting (≤+10 dBm output level)

Variable Sweep

(Available only in dual and tri-modes)

Range

0 to ±30 µA

Sweep Rates

5 to 40 sec

Step Size

5 sec

Accuracy

±0.5 sec/sweep

Phase Shift

Range

0 to 120 degrees in 5 degree increments
(150 Hz phase relative to 90 Hz)

Accuracy

±0.5°

G/S MODE

TONE FREQUENCY ACCURACY

90 Hz ±0.02%
150 Hz ±0.02%

MODULATION

CAL

90 and 150 Hz Tones

40% AM , each tone

Accuracy

±2% modulation

Variable

Range

0% to 50% AM (90 and 150 Hz tones)

Distortion

<2.5% in CAL position

G/S DDM

Fixed

Range

±0, 0.091, 0.175 or 0.400 DDM and tone delete

Accuracy

±0.003 DDM (±2.5 µA) ±3% of setting (≤+10 dBm output level)

Variable

Range

±0.8 DDM in 0.001 DDM steps

Accuracy

±0.0048 DDM (±4.0 µA) ±3% of setting (≤+10 dBm output level)

Phase Shift

Range

0 to 120 degrees in 5 degree increments
(150 Hz phase relative to 90 Hz)

Accuracy

±0.5°

MARKER MODE

MARKER TONE FREQUENCY ACCURACY

400 Hz ±0.02%
1300 Hz ±0.02%
3000 Hz ±0.02%

MODULATION

CAL

Setting

95% AM

Accuracy

±5% modulation

Variable (single carrier only)

Range

0% to 95% AM

Distortion

Single Carrier

<2.5% in CAL position (-67 to +10 dBm)

Tri-Mode

<5% in CAL position

COMM MODE (COMM AM, COMM FM, COMM SSB)

COMM TONE FREQUENCY ACCURACY

Pre-set (AM) 1020 Hz

±0.02%

Pre-set (FM) 1000 Hz

±0.02%

Pre-set (SSB) 1000 Hz / Variable (SSB) 25 to 3000 Hz

±6.25 Hz

Variable Steps (SSB)

25 Hz

AM MODULATION

CAL

1020 Hz tone

30% AM

Accuracy

±2% modulation

Variable

Range

0% to 95% AM (1% steps)

Distortion

<2.5% in CAL position

FM MODULATION

CAL

1000 Hz tone

5 KHz deviation

Accuracy

±0.5 KHz deviation

Variable

Range

1 to 15 KHz (1 KHz steps)

Distortion

<5% in CAL position

SSB MODULATION

USB/LSB offset carrier

SELCAL MODE

Provides amplitude modulation with SELCAL (SElective CALLing) tones

SELCAL TONE FREQUENCY ACCURACY

± 0.02%

TRANSMIT MODES

Single

single transmission

Continuous

7.5 sec interval (typical)

MODULATION

CAL

Per SELCAL Tone

40% AM

Accuracy

±2% modulation

Variable

Range

0% to 55% AM

Distortion

<2.5% in CAL position

EXTERNAL FREQUENCY COUNTER

FREQUENCY RANGE

Antenna and RF I/O Connectors

Range

10 to 400 MHz

Resolution

100 Hz

Accuracy

Same as time base, ±1 count

AUX I/O Connectors

Range

1 to 10 MHz

Resolution

1 Hz

Accuracy

Same as time base, ±1 count

SENSITIVITY

ANT Connector

≥-35 dBm

RF I/O Connector

≥-10 dBm

AUX I/O Connector

≥1 Vp-p

POWER METER (RF I/O CONNECTOR)

FREQUENCY RANGE

10.0 to 400.0 MHz

POWER RANGE

0.1 to <1 W

Resolution 0.01 W

1 to <100 W

Resolution 0.1 W (NOTE 1)

100 to 1999 W

Resolution 1 W (NOTE 1)

Accuracy

<100 MHz

±1.2% of reading, ±1 count, CW only (NOTE 2)

100 to 400 MHz

±8% of reading, ±1 count, CW only (NOTE 2)

DUTY CYCLE

≤10 W, continuous

>10 W to ≤20 W, 3 min on, 2 min off

>20 W to ≤30 W, 1 min on, 2 min off

AM METER

Audio Range

50 to 3000 Hz

Percent Modulation Range

10% to 99%

Accuracy

±10% of reading

Sensitivity

Antenna Connector

≥-20 dBm

RF I/O Connector

≥+5 dBm

FM METER

Audio Range

50 to 3000 Hz

Deviation Range

1 to 15 kHz

Accuracy

±(0.4 kHz + 8% of reading)

Minimum Input Level

Antenna Connector

≥-35 dBm

RF I/O Connector

≥-10 dBm

SWR METER (SWR CONNECTOR)

Frequency Range

10.0 to 410.0 MHz

Accuracy

SWR <3:1

±0.2, ±20% of reading

SWR >3:1

±0.3, ±20% of reading

121.5/243 BEACON MONITOR (OPTION)

Swept Audio Tone Range

100 Hz to 3000 Hz

Accuracy

±10% of reading

Sensitivity**Antenna Connector**

≥ -30 dBm

RF I/O Connector

≥ 0 dBm

406 MHZ BEACON MONITOR (OPTION)

Sensitivity**Antenna Connector**

≥ -35 dBm

RF I/O Connector

≥ -10 dBm

INPUTS/OUTPUTS

RF I/O CONNECTOR**Type**

Input/Output

Impedance

50 Ω typical

Maximum Input Level

30 W, 1 min on, 2 min off

VSWR

10 to ≤300 MHz

<1.3:1

>300 to 400 MHz

<1.35:1

ANTENNA CONNECTOR**Type**

Input/Output

Impedance

50 Ω typical

Maximum Input Level

0.5 W

SWR CONNECTOR**Type**

Output

Impedance

50 Ω typical

Maximum Reverse Power

+25 dBm

VSWR

10 to ≤300 MHz

<1.3:1

>300 to 400 MHz

<1.35:1

AUX CONNECTOR**Type**

Input/Output

Impedance

800 Ω typical

Maximum Input Level

5 Vp-p maximum, 3 VDC maximum

TIMEBASE (TCXO)

Temperature Stability

±1 ppm

Aging

±1 ppm per year

Accuracy

±1 ppm when Auto Cal is performed

BATTERY

Type

Li Ion

Duration

>8 hrs continuous operation

INPUT POWER (TEST SET)

Input Range

11 to 32 Vdc

Power Consumption

55 W maximum

16 W nominal at 18 VDC with charged battery

Fuse Requirements

5 A, 32 VDC, type F

INPUT POWER (SUPPLIED EXTERNAL AC TO DC CONVERTER)

Input Range

100 to 250 VAC, 1.5 A maximum, 47-63 Hz

Main Supply Voltage Fluctuations

≤10% of the nominal voltage

Transient Over-voltages

According to installation category II

ENVIRONMENTAL (TEST SET)

Use

Pollution degree 2

Altitude

≤4800 meters

Operating Temperature (NOTE 3)

-20° to 55°C

Storage Temperature (NOTE 4)

-30° to 70°C

Relative Humidity

80% from 5°C to <10°C
 95% from 10°C to <31°C
 75% from 31°C to <40°C
 45% from 40°C to 50°C

ENVIRONMENTAL (SUPPLIED EXTERNAL AC TO DC CONVERTER)**Use**

Indoors

Altitude

≤3,000 meters

Temperature

5° to 40°C

PHYSICAL CHARACTERISTICS**Dimensions:**

Height

11.2 in (28.5 cm)

Width

9.1 in (23.1 cm)

Depth

2.7 in (6.9 cm)

Weight (Test Set Only)

<8 lbs. (3.6 kg)

SUPPLEMENTAL INFORMATION

Audio distortion characteristics are measured in a 20 Hz to 15 kHz post detection bandwidth.

All DDM measurements are made on RF output signal.

Test Set Certifications

| | | |
|---------------------------------------|----------------|---------------------------|
| Altitude, operating | MIL-PRF-28800F | Class 2 |
| Altitude, not operating | MIL-PRF-28800F | Class 2 |
| Bench Handling | MIL-PRF-28800F | Class 2 |
| Blowing Dust | MIL-STD-810F | Method 510.4, Procedure I |
| Drip-proof | MIL-PRF-28800F | Class 2 |
| Explosive Atmosphere | MIL-STD-810F | Method 511.4, Procedure 1 |
| Relative Humidity | MIL-PRF-28800F | Class 2 |
| Shock, Functional | MIL-PRF-28800F | Class 2 |
| Vibration Limits | MIL-PRF-28800F | Class 2 |
| Temp, operating ^{NOTE 5} | MIL-PRF-28800F | Class 2 |
| Temp, not operating ^{NOTE 6} | MIL-PRF-28800F | Class 2 |
| Transit Drop | MIL-PRF-28800F | Class 2 |

| | |
|-------------------|--|
| Safety Compliance | UL-61010B-1 EN 61010-1 CSA 22.2 No 61010-1 |
| EMC | EN 61326 |

External AC-DC Converter Certifications

| | |
|--------------------|---|
| Safety Compliance | UL 1950 DS CSA 22.2 No. 234 VDE EN 60 950 |
| EMI/RFI Compliance | FCC Docket 20780 Curve "B" |
| EMC | EN 61326 |

Transit Case Certifications

| | | |
|------------------------|--------------|--|
| Drop Test | FED-STD-101C | Method 5007.1 Paragraph 6.3, Procedure A, Level A |
| Falling Dart Impact | ATA 300 | Category I |
| Vibration, Loose Cargo | FED-STD-101C | Method 5019 |
| Vibration, Sweep | ATA 300 | Category I |
| Simulated Rainfall | MIL-STD-810F | Method 506.4 Procedure II of 4.1.2 |
| | FED-STD-101C | Method 5009.1 Sec 6.7.1 |
| Immersion | MIL-STD-810F | Method 512.4 |

VERSIONS AND ACCESSORIES**Ordering Numbers**

4000-110

4000-220

4000OPT1

Versions

IFR 4000 Nav/Comm Ramp Test Set, with US mains leads
 IFR 4000 Nav/Comm Ramp Test Set, with European mains leads
 ELT (121.5/243 MHz beacon and 406 MHz COSPAS/SARSAT beacon test)

Standard Accessories

VHF/UHF multi-band antenna
 Customized transit case
 Operation manual (CD)
 AC/DC power supply
 AC line cord
 TNC (male) to TNC (male) coaxial cable
 TNC short
 Spare fuse

Optional Accessories

| | |
|----------|------------------------------|
| AC0820 | Desk top stand |
| AC0821 | RS-232 cable |
| AC0822CD | 4000 maintenance manual (CD) |
| AC0823CD | 4000 operation manual (CD) |

Extended Standard Warranties with Calibration for 4000

| | |
|------------|---|
| W4000/203C | Extended standard warranty 36 months with scheduled calibration |
| W4000/205C | Extended standard warranty 60 months with scheduled calibration |



NOTES

- Note 1 - External attenuator required for input power greater than 30 W
- Note 2 - Accuracy specification excluding external attenuator
- Note 3 - Battery charging temperature range: 5° to 40°C (controlled by internal charger)
- Note 4 - Li Ion battery must be removed below -20°C and above 60°C
- Note 5 - Temperature range extended to -20°C to 55°C.
- Note 6 - Temperature range reduced to -30°C to 71°C.

CHINA Beijing

Tel: [+86] (10) 6539 1166
Fax: [+86] (10) 6539 1778

CHINA Shanghai

Tel: [+86] (21) 5109 5128
Fax: [+86] (21) 5150 6112

FINLAND

Tel: [+358] (9) 2709 5541
Fax: [+358] (9) 804 2441

FRANCE

Tel: [+33] 1 60 79 96 00
Fax: [+33] 1 60 77 69 22

GERMANY

Tel: [+49] 8131 2926-0
Fax: [+49] 8131 2926-130

HONG KONG

Tel: [+852] 2832 7988
Fax: [+852] 2834 5364

INDIA

Tel: [+91] 80 5115 4501
Fax: [+91] 80 5115 4502

KOREA

Tel: [+82] (2) 3424 2719
Fax: [+82] (2) 3424 8620

SCANDINAVIA

Tel: [+45] 9614 0045
Fax: [+45] 9614 0047

SPAIN

Tel: [+34] (91) 640 11 34
Fax: [+34] (91) 640 06 40

UK Burnham

Tel: [+44] (0) 1628 604455
Fax: [+44] (0) 1628 662017

UK Cambridge

Tel: [+44] (0) 1763 262277
Fax: [+44] (0) 1763 285353

UK Stevenage

Tel: [+44] (0) 1438 742200
Fax: [+44] (0) 1438 727601
Freephone: 0800 282388

USA

Tel: [+1] (316) 522 4981
Fax: [+1] (316) 522 1360
Toll Free: 800 835 2352



As we are always seeking to improve our products, the information in this document gives only a general indication of the product capacity, performance and suitability, none of which shall form part of any contract. We reserve the right to make design changes without notice. All trademarks are acknowledged. Parent company Aeroflex, Inc. ©Aeroflex 2006.

www.aeroflex.com
info-test@eroflex.com



Our passion for performance is defined by three attributes represented by these three icons: solution-minded, performance-driven and customer-focused.