

# PowerLogger 10

## Precision Digital Multimeters, Power Meters

- 300,000 counts and triple display
- Precision multimeter (V, dB, A, W, F, Hz, F, °C/°F, V $\rightarrow$ ←)
- Direct current measurement (to 10 A) or via (clip-on) current transformer: A transformation ratio of 1000:1 or 10,000:1 is accounted for by the display
- Quartz movement for Min-Max recording relative to real-time
- AUTO SELECT  
Automatic recognition of measured quantities (V, W and F)
- Connector jack for external power pack
- Power and energy measurement (W, VAR, VA, Wh, VARh, PF) with analog signals or pulse-type energy measurement, display of momentary measured values, mean values and peak power values
- Power disturbance recording
- Large measurement data memory for up to 60,000 measured values



### Applications

PowerLogger10 multimeter is a power quality troubleshooting tool, as well as a high performance precision instrument for laboratory use, service and training.

With a display range of 300,000 counts, as well as outstanding accuracy and long-term stability, it fulfills all requirements for use in calibration and R&D laboratories.

The instrument can be utilized on-site for precision maintenance and calibration tasks thanks to battery operation.

### Features

#### Convenient Triple Display

The momentary measured value and up to two additional values are displayed simultaneously, for example:

- Momentary, minimum and maximum measured values
- Frequency and RMS value of AC measuring voltage
- Momentary measured values as well as active power, voltage and current
- Maximum value for periodic power with date and time

#### High Resolution and Precision

5 $\frac{3}{4}$  places ( $\geq$  309,999 counts) for DC measured quantities and 4 $\frac{3}{4}$  places ( $\geq$  30,999 counts) for AC measured quantities allow for precision reference measurements and use as a calibration standard for testing devices and assemblies.

#### RMS Value with Distorted Waveshape

The utilized measuring method allows for waveshape independent RMS measurement (TRMS AC and AC+DC) up to 100 kHz, and up to a crest factor of 5.

#### Additional Functions

Continuity testing with acoustic signal, events counting (number and duration), counting of zero-crossings, stopwatch, data-compare and extended-range capacitance measurement. Type J and K thermocouples and platinum sensors can be connected thanks to the integrated temperature measuring function.

#### Overload Protection

The instrument is safeguarded for up to 600 V in all measuring functions by overload protection. An acoustic signal is generated if the upper voltage or current range limit is exceeded.

FUSE appears at the display if the fuse for the current measuring ranges blows.

#### Calibration Certificate

The multimeters are furnished with an internationally valid DKD calibration certificate. After the specified calibration interval has elapsed (recommended interval: 1 year), the multimeters can be recalibrated in our own, or any other accredited DKD calibration laboratory.

# PowerLogger 10

## Precision Digital Multimeters, Power Meters

### Infrared Data Interface

The device can be remote configured, and momentary and saved measurement data can be read out via the bidirectional infrared interface supplied as standard equipment. The RS232 or USB interface adapter

as well as DranWin 10 software, are required to this end (see accessories). Device driver software for LabView is available upon request.

### Automatic Blocking Sockets (ABS) \*

Automatic blocking sockets prevent incorrect connection of measurement cables and inadvertent selection of the wrong measured quantity. This significantly reduces danger to the user, the instrument and the system under test, and in many cases eliminates it entirely.

### Automatic Measured Value Storage with Comparison\*

The DATA function automatically saves the digitally displayed measured value after settling in. Acoustic signaling is also used to indicate whether the new measured value deviates from the initial reference value less or more than 33% of the measuring range.

### Power Saving Circuit

The device is switched off automatically if the measured value remains unchanged for a period of approximately 10 minutes, and if none of the controls are activated during this time.

Automatic shutdown can be deactivated.

### Connector Jack for External Power Supply

Our NA5/600 can be connected for long term measurement, especially in memory mode operation, and for power disturbance recording. As opposed to common plug-in power packs, the NA5/600 includes a regulated output with minimal residual ripple and coupling capacitance to the mains input, as well as a highly insulated power cable. Measurement accuracy influences are thus minimized, and there is no impairment of electrical safety.

\* Patented

## Additional Functions for PowerLogger 10

### Power Measurement

The PowerLogger 10 is a compact power meter for direct and alternating current in single-phase systems. The electrical circuit can be connected either directly, or via a current transformer. If a current transformer is connected to the multimeter (mA or A input), all current and power displays are represented with the correct value based upon the selected transformation ratio of 1000:1 or 10,000:1.

Universal power measurement includes the following measuring functions: active, reactive and apparent power, power factor and energy. Beyond this, the mean power value can be generated over a specified time period (e.g. 15 min.), and the corresponding maximum value can be recorded along with time of occurrence.

### Power Disturbance Recording

The PowerLogger 10 is equipped with a function for acquiring and recording power disturbances which is unique amongst the handheld multimeters. This allows for simultaneous, continuous recording of voltage characteristics and event-triggered recording of voltage dips (> 10 ms) and voltage transients (> 0.5 ms).

One of two different recording and analysis modes can be selected:

1. If a power disturbance occurs, its type, time of occurrence, duration and maximum value are entered to an events list (capacity: 250 events, volatile memory), whose contents can be viewed at the multimeter display.
2. Same as above plus additional recording of measured values to internal measured value memory when events occur (capacity: approx. 60,000 measured values). Memory contents can be read out with DranWin 10 software and analyzed in detail.

### Memory Mode Operation

The PowerLogger 10 is equipped with a quartz-movement synchronized measurement data memory (128 kB), which has enough capacity for 13,000 to 120,000 measured values depending upon configuration. This allows for utilization of the instrument as an autonomous real-time data logger.

Measurement data recording is executed either:

- In a time controlled fashion with an adjustable sampling interval within a range of 0.5 ms (for V DC only) to 10 minutes (see sampling rate in the table on page 3)
- Dependent upon measured value in the event of exceeded limit/delta value
- As an individual measured value by pressing a key

Memory contents can be read out by a PC with the help of the RS232 or the USB adapter, and can be analyzed and documented with DranWin 10 analysis software.

## Applicable Regulations and Standards

DIN EN 61010, part 1:2001, VDE 0411-1:2002	Safety requirements for electrical equipment for measurement, control and laboratory use
DIN EN 61326 VDE 0843, part 20	Electrical equipment for control technology and laboratory use – EMC requirements
DIN EN 60529 DIN VDE 0470, part 1	Test instruments and test procedures – Degrees of protection provided by enclosures (IP code)

## Standard equipment

- 1 multimeter
- 1 protective rubber cover
- 1 cable set:  
KS29 for PowerLogger 10  
(3 safety measurement cables with test probes)
- 2 batteries
- 1 set operating instructions
- 1 DKD calibration certificate

## Guarantee

- 3 years material and workmanship  
1 to 3 years for calibration (depending upon application)

# PowerLogger 10

## Precision Digital Multimeters, Power Meters

### Characteristic Values

Meas. Function	Resolution at Upper Range Limit			Input Impedance		Accuracy Error at Max. Resolution under Reference Conditions		Overload Capacity <sup>4)</sup>		Measuring Rate			
						$\pm(\% \text{ rdg.} + \dots \% \text{ of range} + \dots \text{ d})$	$\pm(\% \text{ rdg.} + \dots \text{ d})$						
	Measuring Range	300,000 <sup>1)</sup>	30,000 <sup>1)</sup>	3000 <sup>1)</sup>	—	$\infty$	—	$\infty$ <sup>5)</sup>	Over-load Value	Over-load Duration	—	$\infty$	~
<b>V</b>	300 mV	1 $\mu$ V	10 $\mu$ V		> 20 M $\Omega$	5 M $\Omega$ // < 50 pF	0.02 + 0.010 + 5 <sup>7)</sup>	0.5 + 30	600 V DC AC RMS sine	Cont.	50 ms	0.5 s	1 s
	3 V	10 $\mu$ V	100 $\mu$ V		11 M $\Omega$	5 M $\Omega$ // < 50 pF	0.02 + 0.005 + 5	0.2 + 30					
	30 V	100 $\mu$ V	1 mV		10 M $\Omega$	5 M $\Omega$ // < 50 pF	0.02 + 0.005 + 5	0.2 + 30					
	300 V	1 mV	10 mV		10 M $\Omega$	5 M $\Omega$ // < 50 pF	0.02 + 0.005 + 5	0.2 + 30					
	600 V	10 mV	100 mV		10 M $\Omega$	5 M $\Omega$ // < 50 pF	0.02 + 0.005 + 5	0.2 + 30					
<b>dB</b>	See table on following page			—	Same as V $\infty$	—	$\pm 0.1 \text{ dB}$ <sup>11)</sup>				1 s		
					Approx. voltage drop at URL								
					—	$\infty$	—	$\infty$ <sup>5)</sup>					
<b>A</b>	300 $\mu$ A	1 nA	10 nA		160 mV	160 mV	0.05 + 0.02 + 5	0.5 + 30	0.36 A	Cont.	50 ms	0.5 s	
	3 mA	10 nA	100 nA		160 mV	160 mV	0.05 + 0.01 + 5	0.5 + 30					
	20 mA	100 nA	1 $\mu$ A		170 mV	170 mV	0.02 + 0.01 + 5	0.5 + 30					
	30 mA			0.05 + 0.01 + 5									
	300 mA	1 $\mu$ A	10 $\mu$ A		300 mV	300 mV	0.1 + 0.01 + 5	0.5 + 30					
	3 A		100 $\mu$ A		110 mV	110 mV	0.2 + 0.05 + 5	0.7 + 30 <sup>12)</sup>					
10 A		1 mA		350 mV	350 mV	0.2 + 0.05 + 5	0.5 + 30						
					Open-circuit voltage	Meas. current at URL	$\pm(\% \text{ rdg.} + \dots \% \text{ of range} + \dots \text{ d})$						
<b><math>\Omega</math></b>	300 $\Omega$	1 m $\Omega$			0.6 V	Max. 250 $\mu$ A	0.05 + 0.01 + 5 <sup>7)</sup>	600 V DC AC RMS Sine	10 min.	0.5 s			
	3 k $\Omega$	10 m $\Omega$			0.6 V	Max. 45 $\mu$ A	0.05 + 0.01 + 5 <sup>7)</sup>						
	30 k $\Omega$	100 m $\Omega$			0.6 V	Max. 4.5 $\mu$ A	0.05 + 0.01 + 5						
	300 k $\Omega$	1 $\Omega$			0.6 V	Max. 1.5 $\mu$ A	0.05 + 0.02 + 5						
	3 M $\Omega$	10 $\Omega$			0.6 V	Max. 150 nA	0.1 + 0.02 + 5						
	30 M $\Omega$	100 $\Omega$			0.6 V	Max. 15 nA	1 + 0.2 + 5						
<b><math>\Omega</math> <math>\rightarrow</math></b>	300 $\Omega$			0.1 $\Omega$	Max. 3 V	Max. 1 mA	1 + 0 + 3						
<b><math>\rightarrow</math> <math>\rightarrow</math></b>	300 mV			100 $\mu$ V	Max. 3 V	Max. 1 mA	0.2 + 0 + 3				50 ms		
<b><math>\rightarrow</math></b>	3 V			100 $\mu$ V	Max. 3 V	Max. 1 mA	0.2 + 0 + 3				50 ms		
					Discharge res.	$U_{0 \text{ max}}$	$\pm(\% \text{ rdg.} + \dots \% \text{ of range})$						
<b>F</b>	3 nF			1 pF	10 M $\Omega$	3 V	1.0 + 0.2 <sup>7)</sup>	600 V DC AC RMS Sine	10 min.	2 s			
	30 nF			10 pF	10 M $\Omega$	3 V	1.0 + 0.2 <sup>7)</sup>						
	300 nF			100 pF	1 M $\Omega$	3 V	1.0 + 0.2						
	3 $\mu$ F			1 nF	100 k $\Omega$	3 V	1.0 + 0.2						
	30 $\mu$ F			10 nF	11 k $\Omega$	3 V	1.0 + 0.2						
	300 $\mu$ F			100 nF	2 k $\Omega$	3 V	5.0 + 1						
	3,000 $\mu$ F			1 $\mu$ F	2 k $\Omega$	3 V	5.0 + 1						
	30,000 $\mu$ F			1 $\mu$ F	2 k $\Omega$	3 V	5.0 + 1						
				$f_{\text{min}}$ <sup>3)</sup>			$\pm(\% \text{ rdg.} + \dots \text{ d})$						
<b>Hz</b>	300.000 Hz	0.001 Hz			1 Hz		0.05 + 1 <sup>8)</sup>	600 V	Cont.	1 s			
	3.00000 kHz	0.01 Hz			1 Hz		0.05 + 1 <sup>8)</sup>	600 V					
	300.000 kHz	1 Hz			1 Hz		0.05 + 1 <sup>8)</sup>	300 V 30 V					
	100 min. <sup>2)</sup>		100 ms (1/10 s)					600 V					
							$\pm(\% \text{ rdg.} + \dots \text{ d})$						
<b><math>^{\circ}</math>C/<math>^{\circ}</math>F</b>	Pt 100/ Pt 100 0	-200.0 ... +100.0 $^{\circ}$ C	0.1 $^{\circ}$ C				0.5 K + 3 <sup>9)</sup>	600 V DC RMS sine	10 min.	0.5 s			
		+100.0 ... +850.0 $^{\circ}$ C					0.2% + 3 <sup>9)</sup>						
	K NiCr- Ni C	-270.0 ... +1372.0 $^{\circ}$	0.1 $^{\circ}$ C				0.7 + 3 <sup>9, 10)</sup>	600 V DC RMS sine					
J Fe- CuNi	-210.0 ... +1200.0 $^{\circ}$	0.1 $^{\circ}$ C				0.8 + 3 <sup>9, 10)</sup>	600 V DC RMS sine						

1) Display: 5¼-place for DC and 4¼-place for AC  
 2) Stopwatch format: mm:ss:hh where m = minutes, s = seconds and h = hundredths of a second, max. 99:59:59, key operation only  
 3) Lowest measurable frequency for sinusoidal measuring signals symmetrical to zero point  
 4) At 0° ... + 40°C  
 5) Values of less than 100 counts are suppressed, 16 ... 45 ... 65 Hz ... 100 kHz sinusoidal. See influence error on page 4.  
 6) 12 A – 5 min., 16 A – 30 s  
 7) ZERO is displayed for “zero balancing” function.  
 8) Range 300mV  $\infty$ :  $U_E = 50 \text{ mV}_{\text{RMS}} \dots 300 \text{ mV}_{\text{RMS}}$   
 3 V  $\infty$ :  $U_E = 0.3 \text{ V}_{\text{RMS}} \dots 3 \text{ V}_{\text{RMS}}$   
 30 V  $\infty$ :  $U_E = 3 \text{ V}_{\text{RMS}} \dots 30 \text{ V}_{\text{RMS}}$   
 300 V  $\infty$ :  $U_E = 30 \text{ V}_{\text{RMS}} \dots 300 \text{ V}_{\text{RMS}}$   
 600 V  $\infty$ :  $U_E = 300 \text{ V}_{\text{RMS}} \dots 600 \text{ V}_{\text{RMS}}$   
 For voltages > 100 V: power limiting of  $3 \cdot 10^6 \text{ V} \cdot \text{Hz}$

9) Plus sensor deviation  
 10) Without integrated reference junction, additional error with internal reference junction:  $\pm 2 \text{ K}$   
 11) For  $U > 10\%$  of the measuring range  
 12) Applicable as from 500 counts  
 Key: rdg. = measured value (reading), d = digit, URL = upper range limit

**Real-Time Clock**  
 Accuracy  $\pm 1 \text{ min./month}$   
 Temperature Influence  $50 \text{ ppm/K}$

# PowerLogger 10

## Precision Digital Multimeters, Power Meters

### db Ranges

Measuring Ranges	Display Range at Reference Voltage $U_{REF} = 0.775 V$	Resolution
300mV ~	-48 dB ... -8 dB	0.01 dB
3 V ~	-38 dB ... +12 dB	0.01 dB
30 V ~	-18 dB ... +32 dB	0.01 dB
300 V ~	+2 dB ... +52 dB	0.01 dB
600 V ~	+22 dB ... +63 dB	0.01 dB
	Display (dB) = $20 \lg U_x(V) / U_{REF}$	

### AUTO SELECT: Automatic Measured Quantity Recognition

Measured Quantity	Measuring Range Recognition	Condition	Recog. Time
Voltage V $\approx$	$V_{RMS} > 0.81 V \dots 600 V$	—	1 s
Voltage V ~	$V_{RMS} > 1 V \dots 600 V$	Frequency > 20 Hz	1 s
Resistance	$0 \Omega \dots 15 M\Omega$	—	1 s
Capacitance	$> 1.5 nF \dots 300 \mu F$	Electrolytic capacitor must be correctly connected	1 s
Diode	Voltage in conducting direction: max. 1 V	Diode must be correctly connected: anode to $\rightarrow$	1 s

### Power Measurement

Measuring Function	Measuring Range	Switch Setting		Resolution at Upper Range Limit	Overload Capacity at 0 ... +40° C	
		mA	A		Overload Value	Overload Duration
<b>W, Var, VA</b>	1 mW	1		0.1 $\mu W$	V: 600 V mA: 0.36 A A: 10 A	V / mA: cont. 10 A: cont. 12 A: 5 min. 16 A: 30 s
	10 mW	1		1 m $\Omega$		
	100 mW	1		10 m $\Omega$		
	1 W	1		0.1 mW		
	10 W	1	1	1 mW		
	100 W	1	1	10 mW		
	1 kW	1	1	0.1 W		
	10 kW		1	1 W		

### Accuracy and Frequency Influence for Power and Energy Measurement

Measured Quantity	Measuring Range	Intrinsic Error (... % rdg. + ... d)		
		15 Hz ... 45 Hz	45 Hz ... 65 Hz	65 Hz ... 1 kHz
Active power	300 mA ... 10 A	1.3+20	1+20	3+20
Reactive power		2.5+20	1.5+20	3+20
Apparent power		1.2+20	1+20	1.2+20
Power factor	$\pm(0.02 \dots 1)$	2+2	1+2	2+2
¼ hour power		1.2+20	1+20	1.3+20
Energy		1.2+2	1+2	1.3+2
Voltage		0.4+30	0.3+30	0.4+30
Current		0.7+30	0.6+30	0.9+30

### Mains Monitoring

Type of Disturbance	Measuring Range	Resolution	Intrinsic Error under Reference Conditions	Disturbance Acquirable as of
Dropout*	300 $V_{RMS}$	4 V	5% rdg. + 5% of range	10 ms
	600 $V_{RMS}$	40 V	10% rdg. + 10% of range	
$\pm$ Pulse *	200 ... 1000 $V_S$	10 V	50 V	0.5 ... 5 $\mu s$

\* Adjustable trigger threshold

### Influencing Quantities and Influence Error

Influencing Qty.	Sphere of Influence	Measured Qty/Meas. Range	Influence Error ppm/K
Temperature	$0^\circ C \dots +21^\circ C$ and $+25^\circ C \dots +40^\circ C$	V $\approx$	30
		V ~	50
		300 $\mu A \dots 30 mA \approx + \approx$	180
		300 mA $\approx + \approx$	290
		3 A / 10 A $\approx + \approx$	200
		300 $\Omega \dots 300 k\Omega$	100
		3 M $\Omega$	200
		30 M $\Omega$	1000
		3 nF ... 30 $\mu F$	500
		Hz	50
$^\circ C$	100		

Influencing Qty.	Sphere of Influence	Measured Qty/Meas. Range	Influence Error
Relative Humidity	75%, 3 days, instrument off	V, A, $\Omega$ , F, Hz, $^\circ C$	1 x intrinsic error

Influencing Quantity	Frequency	Measured Qty. / Measuring Range	Influence Error <sup>2)</sup> $\pm(\% \text{ rdg.} + \dots \text{ d})$
Frequency $V_{AC}$	> 15 Hz ... 45 Hz	300.000 mV	2 + 10 d
	> 65 Hz ... 1 kHz		0.5
	> 1kHz ... 10 kHz		1
	> 10kHz ... 50 kHz		3
	> 50kHz ... 100kHz		10
	> 15 Hz ... 45 Hz		3.00000 V 30.0000 V 300.000 V
	> 65 Hz ... 1 kHz	0.5	
	> 1kHz ... 20 kHz	1.5	
	> 20kHz ... 100kHz	5	
	Frequency $I_{AC}$	> 15 Hz ... 45 Hz	600.00 V
> 65 Hz ... 1 kHz		1	
> 1kHz ... 10 kHz		10	
> 15 Hz ... 45 Hz		300 $\mu A$ ...	2 + 10
> 65 Hz ... 5 kHz			0.75 + 5
> 5kHz ... 10 kHz			5 + 5
> 15 Hz ... 45 Hz		3 A	2 + 10
> 65 Hz ... 1 kHz			29S: 0.75 + 5
> 1kHz ... 10 kHz			5 + 5
> 15 Hz ... 45 Hz		10 A	2 + 10
> 65 Hz ... 2 kHz	0.75 + 5		
> 2kHz ... 10 kHz	5 + 5		

Influencing Qty.	Sphere of Influence	Measured Qty/Meas. Range	Influence Error <sup>3)</sup>
	Crest Factor CF	1 ... 3	$\pm 1\% \text{ rdg.}$
		> 3 ... 5	$\pm 3\% \text{ rdg.}$
Measured Quantity Waveshape	Allowable crest factor CF of the periodic quantity to be		
<p>Current and Voltage Measure-</p>			

# PowerLogger 10

## Precision Digital Multimeters, Power Meters

Influencing Qty.	Sphere of Influence	Measuring Range	Attenuation ±dB
Common Mode Interference Voltage	Interference quantity max. 600 V ~	V $\overline{\sim}$	> 90 dB
	Interference quantity max. 600 V ~ 50 Hz, 60 Hz sine	300 mV ... 30 V ~	> 80 dB
		300 V ~	> 70 dB
Series Mode Interference Voltage	Interference quantity: V ~, resp. nominal value of the measuring range, max. 600 V ~, 50 Hz, 60 Hz sine	V $\overline{\sim}$	> 60 dB
	Interference quantity max. 600 V $\overline{\sim}$	V ~	> 60 dB

1) With zero balancing

2) Specified accuracy valid as of display values of 10% of the measuring range

3) Except for sinusoidal waveshape

### Reference Conditions

Ambient Temperature	+73 °F (+23 °C) ±2 °
Relative humidity	40 ... 60%
Measured qty. frequency	45 ... 65 Hz
Measured quantity waveshape	Sine
Battery voltage	3 V ±0.1 V
Adapter voltage	5 V ±0.2 V

### Response Time (after manual range selection)

Measured Quantity / Measuring Range	Digital Display Response Time	Measured Quantity Jump Function
V $\overline{\sim}$ , V ~, A $\overline{\sim}$ , A ~	1.5 s	from 0 to 80% of upper range limit
300 Ω ... 3 MΩ	2 s	from ∞ to 50% of upper range limit
30 MΩ	5 s	
Continuity	< 50 ms	
$\rightarrow$	1.5 s	from 0 to 50% of upper range limit
3 nF ... 300 μF	Max. 2 s	
3 000 μF	Max. 7 s	
30 000 μF	Max. 14 s	
>10 Hz	Max. 1.5 s	
°F / °C	Max. 3 s	

### Display

LCD panel (65 x 30 mm) with display of up to 3 measured values, unit of measure, type of current and various special functions.

Display / Char. Height 7-segment characters  
Main display: 12 mm  
Auxiliary displays: 7 mm

Number of places 5<sup>3</sup>/<sub>4</sub>-place  $\cong$  309,999 steps

Overflow display "OL" appears

Polarity display "—" sign is displayed if plus pole is connected to "⊥"

Refresh rate Same as sampling rate (see table), but not more than twice per second

### Power Supply

Battery	2 ea. 1.5 V mignon cell (2 ea. size AA) Alkaline manganese per IEC LR6 Zinc-carbon battery per IEC R6
Service life	Alkaline manganese: approx. 100 hours Zinc-carbon: approx. 50 hours
Battery test	$\rightarrow$ is displayed automatically if battery voltage drops to below approx. 2.3 V.
External supply	3.5 ... 5 V~, max. 35 mA, see accessories for suitable power pack
Battery Life	~100 hours

### Electrical Safety

Safety class	II per EN 61010-1:2001/VDE 0411-1:2002	
Measuring category	III	IV
Operating voltage	600 V	300 V
Fouling factor	2	2
Test voltage	5.2 kV~ per IEC/EN 61010-1:2001/ VDE 0411-1:2002	



CAT IV



DKD Calibration Certificate

### Fuses

Fuse links for ranges Up to 300 mA	FF (UR) 1,6 A / 1000 V AC/DC, 6.3 x 32 mm, switching capacity: 10 kA at 1000 V, protects all current measuring ranges up to 300 mA in combination with power diodes
Up to 10 A	FF (UR) 10 A / 1000 V AC/DC, 10 x 38 mm, switching capacity: 30 kA at 1000 V, protects the 3 and 10 A ranges

### Electromagnetic Compatibility (EMC)

Interference emission	EN 61326-1:2002 class B
Interference immunity	EN 61326:2002
	IEC 61000-4-2:1995 + A1:1998 8 kV atmospheric discharge 4 kV contact discharge
	IEC 61000-4-3:1995 + A1:1998 3 V/m
	IEC 61000-4-4:1995 0.5 kV

# PowerLogger 10

## Precision Digital Multimeters, Power Meters

### Ambient Conditions

Operating temp.	-4° F (-20° C) - 122° F (+56° C) -
Storage temp.	-13° F (-25° C) - 158° F (+70° C)
Relative humidity	Max. 75%, no condensation allowed
Elevation	6500 ft (2000 m)

### Mechanical Design

Housing	Impact resistant plastic (ABS)
Dimensions	3.3 x 7.7 x 1.4 in (84 x 195 x 35 mm)
Weight	approx. 0.892 lbs with batteries

Protection Housing: IP 50  
Extract from table on the meaning of IP codes

IP XY (1 <sup>st</sup> digit X)	Protection against foreign object entry	IP XY (2 <sup>nd</sup> digit Y)	Protection against the penetration of water
5	dust protected	0	not protected

### Data Interface

Type	Optical via infrared light through the housing
Data transmission	Serial, bidirectional (not IrDa compatible)
Protocol	Device specific
Baud Rate	8192/9600 baud (selectable)
Functions	<ul style="list-style-type: none"> <li>- Select / query measuring functions and parameters</li> <li>- Query / transmit current measurement data</li> <li>- Read out stored measurement data</li> </ul>

### Accessories for operation at a PC

PowerLogger 10 RS232 Interface Adapter multimeter can be configured from a PC, and measured data can be transferred live to the PC with the help of the BD232 bidirectional adapter. The adapter has no memory of its own. It can be used to read out data from integrated memory in the PowerLogger 10. Up to 6 adapters can be cascaded for the creation of a multi-channel measuring system.



Adapters can be cascaded (combination with the BD232 as well) in order to create a multi-channel system.

#### Memory Capacity:

128 kB (corresponds to roughly 60,000... 120,000 measured values, depending upon measuring function and measured value dynamics)

#### Adjustable Sampling Rate:

50 ms ... 1 min.

### USB Interface Adapter

This adapter is functionally identical to the BD232 interface adapter, although bidirectional transmission takes place between the IR and the USB interface in this case.

*It is not possible to set up a multi-channel system with this adapter.*



### DranWin 10

DranWin 10, PC software is a multilingual data logging program for recording, visualizing, evaluating and documenting measured values acquired. Communications between the PC and the measuring instrument(s) is established via available interfaces and memory adapters. Telephone modems can be interconnected as well.


Depending upon device type, one or several of the following operating modes are possible:

- **Device Configuration**  
Remote configuration and querying of device-specific functions and parameters, for example measuring function, measuring range and memory parameters. Frequently used device settings can be saved to configuration files for easy recall.
- **Online Recording of Measurement Data**  
Read-in, display and recording of current measurement data from the interconnected device
  - Measuring channels Up to 10
  - Start recording Manual, triggered by measured value, time triggered
  - Recording mode
    - > Time controlled with sampling interval of 0.05 s\* ... 1 s ... 60 min.
    - > Manually controlled
    - > Measured-value controlled in the event of exceeded limit/delta value
  - Recording duration Max. 10 million intervals
- \* Depending upon device type, measuring function, number of measuring channels and communication mode (e.g. via modem), sampling intervals of less than 1 second cannot be used.
- **Reading Out and Visualizing Stored Data**  
If supported by the device: read-in and display of offline data recorded to device memory


# PowerLogger 10 Precision Digital Multimeters, Power Meters

For purposes of analysis, data recorded online or read in from the device's memory can be displayed in various formats:


Y(t) Recorder Display  
for Up to 6 Channels




XY Recorder Display  
for Up to 4 Channels



Multimeter Display  
for Up to 4 Channels



Tabular Display  
for Up to 10 Channels



## System Requirements

DranWin 10 (version 5.x) can be run on IBM compatible PCs with Microsoft Windows® 95, 98, ME, NT 4.0, 2000 or XP.

## Accessories

HC30 Hard Case

For multimeters

(with/without GH18 protective rubber cover) and accessories



## Order Information

Designation	Type	Article Number
Precision digital multimeter and power meter including cable set, RS-232 interface adapter, power supply, 10 pack of fuses, hardware case, and DranWin 10 software.	PowerLogger 10 Pack	PPL1
Precision digital multimeter and power meter including cable set, RS-232 interface adapter, power supply, 10 pack of fuses, hardware case, and DranWin 10 software. Plus one 150A CT and one waterproof thermocouple -30 to 220 degrees C.	PowerLogger 10 CT	PPL2



Dranetz-BMI

1000 New Durham Road

Edison, NJ 08818 USA

Phone - 1 - 800 - 372 - 6832

Fax - 1 - 732 - 248 - 1834

sales@dranetz-bmi.com

www.dranetz-bmi.com